

## AMS error codes description (M-Bus, IEC 62056-21, S0, IN, ONF)

| General AMS errors |   |
|--------------------|---|
| 0                  | - without error                         |
| 1                  | - error of input data                   |
| 2                  | - error of output data                  |
| 3                  | - protocol cannot be used for this port |
| 4                  | - readout not started                   |

M-Bus AMS errors

|        |   |
|--------|---|
| 131072 | - non specific error (internal error of module)   |
| 131073 | - readout was stopped by user   |
| 131074 | - bad format address and speed of the device  |
| 131075 | - parameters of the port were not set   |
| 131076 | - message "SND_NKE" was not send in defined time interval to the device   |
| 131077 | - message "SND_NKE" was not send in defined time interval to the device   |
| 131078 | - timeout - receiving "SND_NKE" message response  |
| 131079 | - bad frame when receiving "SND_NKE" message from the device  |
| 131080 | - message "REQ_UD2" was not send  |
| 131081 | - message "REQ_UD2" was not send  |
| 131082 | - timeout - receiving "REQ_UD2" message response  |
| 131083 | - incorrect communication frame for "REQ_UD2" message   |
| 131084 | - incorrect response for "REQ_UD2" message  |
| 131085 | - incorrect device address in response for "REQ_UD2" message  |
| 131086 | - message "SND_UD slave selection" was not send in defined time interval  |
| 131087 | - message "SND_UD slave selection" was not send in defined time interval  |
| 131088 | - timeout - receiving "SND_UD slave selection" message response   |
| 131089 | - bad frame for "SND_UD slave selection" response message   |
| 131090 | - message "SND_UD slave selection" was not send in defined time interval during searching slaves on bus             |
| 131091 | - message "SND_UD slave selection" was not send in defined time interval during searching slaves on bus             |
| 131092 | - message "REQ_UD2" was not send in defined time interval during searching slaves on bus                            |
| 131093 | - message "REQ_UD2" was not send in defined time interval during searching slaves on bus                            |
| 131094 | - collision of secondary addresses during searching slaves on bus (two or more devices have same secondary address) |
| 131329 | - bad first "start" byte for device´s response message  |
| 131330 | - bad second "start" byte for device´s response message   |
| 131331 | - bad first "stop" byte for device´s response message   |
| 131332 | - bad checksum of the response frame  |
| 131333 | - bad value of the response frame length  |
| 131334 | - bad value of the response frame length  |

| IEC 62056-21 AMS errors |   |
|-------------------------|---|
| 65536                   | - internal error  |
| 65537                   | - readout was stopped by user   |
| 65538                   | - bad format address of the device  |
| 65539                   | - not supported character, that describe communication speed in the device answer                           |
| 65540                   | - communication port was not set  |
| 65541                   | - timeout - Identification message not arrived  |
| 65542                   | - the device using unsupported AMS mode   |
| 65543                   | - timeout - Acknowledgement/option select message   |
| 65544                   | - speed was not set   |
| 65545                   | - timeout while receiving two consecutive characters of the message   |
| 65546                   | - timeout while receiving two messages  |
| 65793                   | - not supported character in the field "Manufacturer's identification" of received "Identification message" |
| 65794                   | - not supported character in the field Baud rate identification of received "Identification message"        |
| 65795                   | - not supported character in the field Identification of received "Identification message"                  |
| 65796                   | - not supported character in the fields "CR" and "LF" of received "Identification message"                  |
| 66049                   | - not supported character in the field "Data block" of received "Data message"                              |
| 66050                   | - internal AMS buffer overflow because too long "Data block" of received "Data message"                     |
| 66051                   | - not supported character in the fields "CR" and "LF" of received "Data message"                            |
| 66052                   | - not supported character in the field "ETX" of received "Data message"                                     |
| 66053                   | - field "BCC" of received "Data message" is not equal to calculated check character                         |

| Inputs AMS errors |   |
|-------------------|---|
| 8388608           | - non specific error (internal error of module)                               |
| 8388609           | - readout was stopped by user   |
| 8388610           | - bad format address of the device  |
| 8388611           | - timeout (message was not sent in defined time)                              |
| 8388612           | - timeout (message was not sent in defined time)                              |
| 8388613           | - timeout - receiving message response  |
| 8388865           | - bad frame in answer message   |
| 8388866           | - bad sequential number of the frame  |
| 8388867           | - answer is too long (not enough space for this frame in internal AMS memory) |
| 8388868           | - bad CRC   |
| 8388869           | - bad value in sync. field  |

| Pseudo AMS errors - ONF |   |
|-------------------------|---|
| 65280                   | - non specific error (internal error of module)                               |
| 65281                   | - user set more M-Bus slave devices, that can be handled by AMS functionality |
| 65282                   | - error appeared during slave detection on M-Bus                              |
| 65283                   | - error appeared during reading results of detected slave M-Bus devices       |
| 65284                   | - unsuccessful deleting devices from AMS table                                |
| 65285                   | - error - parsing of detected slave units on M-Bus                            |
| 65286                   | - user defined difrerent number slave units, that were detected on M-Bus      |
| 65287                   | - detected M-Bus unit cannot be add AMS table                                 |
| 65288                   | - SMS message limit   |

More product information:

2N<sup>®</sup> SmartCom (Official Website 2N)

2N<sup>®</sup> SmartCom PRO (Official Website 2N)